

VLT® Soft Starter MCD 500



VLT® Soft Starter MCD 500 is a total motor starting solution. Current transformers measure motor current and provide feedback for controlled motor ramp profiles.

AAC, the Adaptive Acceleration Control automatically employs the best starting and stopping profile for the application.

Adaptive Acceleration Control means, that for each start and stop, the soft starter compares and adapts the process to the chosen profile fitting to the application.

The VLT® Soft Starter MCD 500 has a four line graphical display and a logic keypad making programming easy. Advanced setup is possible displaying operational status.

Three menu systems: Quick Menu, Application Setup and Main Menu provide optimum programming approach.

The perfect solution, also for more severe applications:

- Pumps
- Conveyors
- Fans
- Mixers
- Compressors
- Centrifuge
- Mill
- Saw
- · And many more


Power range

21 – 1600 A, 7,5 – 800 kW (1,2 MW inside Delta Connection) Versions for 200 – 690 VAC



Features Benefits · Automatically adapts to the best starting · AAC Adaptive Acceleration Control and stopping profile for the application • Adjustable Bus Bars, allow for top, bottom · Space saving, reduced cable cost or both (>=360A) and easy retrofitting DC injection braking distributed evenly Reduced installation cost and over three phases less stress on the motor Smaller soft starter can be selected · Inside Delta (6-wire connection) for the application Log Menus, 99 Events and Trip log provide · Eases analysis on the application information on events, trips and performance · Auto Reset · Less down time • Jog (slow-speed operation) Application flexibility Allows motor to be used to its full potential · Second-order thermal model without damage from overloading • Saves space and wiring compared to external bypass Internal bypass contactors (<= 110kW) Very little heat dissipates when running. Eliminates costly external fans, wiring or bypass contactors · Auto-start/stop clock · Application flexibility Compact size - amongst the smallest Saves space in cabinets and other in their class application setups Optimum programming approach and · 4-line graphical display setup for viewing operational status Simplifies the programming, but still Multiple programming setup (Standard Menu, Extended Menu, Quick Set) holding to maximum flexibility • Multiple (8) languages · Serving the whole world





Fully featured Soft Starter for motors up to 800 kW

- Total motor starting solution
- Advanced start, stop and protection features
- Adaptive Acceleration Control
- Inside Delta connection
- 4 line graphical display
- Multiple programming setup menus

Optional:

- Modules for serial communication:
 - DeviceNet
 - Profibus
 - Modbus RTU
 - USB
- · Remote operator kit
- PC software



Remote operation kit

- · Start/stop, reset
- LED for start, run, trip
- Trip codes
- Current display
- Motor temperature display
- 4 20 mA output



Specifications

Supply	
Mains voltage (L1, L2, L3)	
MCD5-xxxx-T5	200 VAC ~ 525 VAC (± 10%)
MCD5-xxxx-T7	380 VAC \sim 690 VAC (\pm 10%) (earthed star supply system only)
MCD5-xxxx-T7	$380 \text{VAC} \sim 600 \text{VAC} (\pm 10\%) (inside delta connection)$
Control voltage (A4, A5, A6)	
CV1 (A5, A6)	24 VAC/VDC (± 20%)
CV2 (A5, A6)	110~120 VAC (+ 10% / - 15%)
CV2 (A4, A6)	220~240 VAC (+ 10% / - 15%)
Mains frequency	50/60 Hz (± 10%)
Rated insulation voltage to earth	600 VAC
Rated impulse withstand voltage	4 kV
Form designation	Bypassed or continuous, semiconductor motor starter form 1

Short circuit capability	
Coordination with semiconductor fuses	Type 2
Coordination with HRC fuses	Type 1
MCD5-0021B to MCD5-0105B	prospective current 10 kA
MCD5-0131B to MCD5-0245C	prospective current 18 kA
MCD5-0360C to MCD5-0927C	prospective current 85 kA
MCD5-1200C to MCD5-1600C	prospective current 100 kA
MCD5-0021B to MCD5-0105B MCD5-0131B to MCD5-0245C MCD5-0360C to MCD5-0927C	prospective current 10 kA prospective current 18 kA prospective current 85 kA

Electromagnetic capability (compliant with EU Directive 89/336/EEC)	
EMC Emissions(Terminals 13 & 14)	IEC 60947-4-2 Class B and Lloyds Marine No. 1 Specification
EMC Immunity	IEC 60947-4-2

Outputs	
Relay Outputs	10A @ 250 VAC resistive, 5A @ 250 VAC AC15 pf 0.3
Programmable Outputs	
Relay A (13, 14)	Normally open
Relay B (21, 22, 24)	Changeover
Relay C (33, 34)	Normally open
Analog Output (07, 08)	0-20 mA or $4-20$ mA (selectable)
Maximum load	600Ω (12 VDC @ 20 mA) (accuracy \pm 5%)
24 VDC Output (16, 08) Maximum load	200 mA (accuracy \pm 10%)

Environmental	
Protection MCD5-0021B ~ MCD5-0105B	IP 20 & NEMA, UL Indoor Type 1
Protection MCD5-0131B ~ MCD5-1600C	IP 00, UL Indoor Open Type
Operating temperature	-10° C to 60° C, above 40° C with derating
Storage temperature	-25°Cto+60°C
Operating Altitude	0 – 1000 m, above 1000 m with derating
Humidity	5% to 95% Relative Humidity
Pollution degree	Pollution Degree 3

Trairinaity	370 to 3370 Helative Harrianty	
Pollution degree	Pollution Degree 3	
5		
Heat Dissipation		
During start	4.5 watts per ampere	

Dimensions

Current rating [A]	Weight [kg]	Height [mm]	Width [mm]	Depth [mm]
21, 37, 43 and 53	4.2			
68	4.5	295	150	183
84, 89 and 105	4.9			
131, 141, 195 and 215	14.9	438	275	250
245	23.9	460	390	279
360, 380 and 428	50.1	689	420	202
595, 619, 790 and 927	53.1		430	302
1200, 1410 and 1600	120	856	585	364

Danfoss can accept no responsibility for possible errors in catalogues, brochures and other printed material. Danfoss reserves the right to alter its products without notice. This also applies to products already on order provided that such alterations can be made without subsequential changes being necessary in specifications already agreed.

All trademarks in this material are property of the respective companies. Danfoss and the Danfoss logotype are trademarks of Danfoss A/S. All rights reserved.